


I/O TERMINAL	DESCRIPTION - TYPE	CONNECTION
TB1(+/-)	POS/NEG OUTPUT TERMINALS - CU-ALUMINUM COMPRESSION LUG	#14-6 AWG.
REM SENSE(+/-)	POS/NEG REMOTE SENSE TERMINALS - 10-32 SCREW HARDWARE	#10 RING LUG
(2) TB1-GND	GROUND TERMINAL - CU-ALUMINUM COMPRESSION LUG	#14-6 AWG.
TB1-L1/L2	AC INPUT TERMINALS - CU-ALUMINUM COMPRESSION LUG	#14-6 AWG.
TB3	SUMMARY ALARM TERMINAL BLOCK - SOLDERLESS COMPRESSION	#22-14 AWG.
TB4	AUXILIARY ALARM TERM BLOCK - SOLDERLESS COMPRESSION	#22-14 AWG.
TB8	TEMPCO PROBE (A10) INTERCONNECTION TERMINAL BLOCK	#22-14 AWG.

- NOTES:**
- FOR DETAIL VIEWS OF ALL PC BOARDS (A1, A5, etc.) SEE DRAWING JE5030-19.
  - I/O PANEL PROTECTION (SHOWN ONLY ON DETAIL) CONSISTS OF EMI FILTER CAPACITORS (C4 & C5) AND SURGE SUPPRESSORS (VR1, VR2, VR4, VR5, VR6 & VR7).
  - DATA NAMEPLATE IS LOCATED ON EXTERIOR LEFT SIDE WALL OF ENCLOSURE. USER'S MANUAL POCKET IS LOCATED ON EXTERIOR RIGHT SIDE WALL OF ENCLOSURE.
  - SAFETY COVER DISPLAYS COMPONENT LAYOUT DIAGRAM, SCHEMATIC & INSTALLATION NOTES.
  - BATTERY ELIMINATOR FILTER CAPACITOR (C2) IS NORMALLY LOCATED IN FRONT OF C1. 130VDC-12ADC THRU 130VDC-25ADC UNITS UTILIZE TWO (2) C1s, THEREFORE C2 IS SHIFTED TO LOWER RIGHT-HAND CORNER OF ENCLOSURE AS SHOWN.
  - IF AT10.1 HAS 480VAC INPUT, OR IS CUSTOMER-SPECIFIED WITH MEDIUM/HIGH AMPERE INTERRUPTING CAPACITY CIRCUIT BREAKERS, CB1 AND CB2 ARE RELOCATED TO PENTHOUSE ENCLOSURE, AND TB6 IS ADDED.

AT10.1 GROUP I STANDARD COMPONENTS

SYMBOL	DESCRIPTION	SYMBOL	DESCRIPTION
A1	MAIN CONTROL PRINTED CIRCUIT BOARD	VR4	AC INPUT SURGE SUPPRESSOR (L1 TO GND)
A6	RECTIFIER ASSY (A3/A16/HEATSINK)	VR5	AC INPUT SURGE SUPPRESSOR (L2 TO GND)
C4	DC OUTPUT EMI FILTER CAPACITOR	VR6	DC OUTPUT SURGE SUPPRESSOR (- TO GND)
C5	DC OUTPUT EMI FILTER CAPACITOR	VR7	C OUTPUT SURGE SUPPRESSOR (+ TO GND)
CB1	AC INPUT CIRCUIT BREAKER (M/H AIC)	<b>OPTIONAL COMPONENTS</b>	
CB2	DC OUTPUT CIRCUIT BREAKER (M/H AIC)	A5	AUXILIARY ALARM RELAY PC BOARD
L1	MAIN INDUCTOR	A10	EXTERNAL TEMPERATURE COMPENSATION PROBE
R2	CURRENT RATING RESISTOR	C1	FILTER CAPACITOR
R3A/B	BALLAST RESISTORS (130 VDC)	C2	BATTERY ELIMINATOR FILTER CAPACITOR
R4	SCALING RESISTOR (POSITIVE LEG)	CR1	POLARITY DIODE
R6	VOLTAGE CROWBAR RESISTOR	CR2	BLOCKING DIODE
R14	SCALING RESISTOR (NEGATIVE LEG)	F1	AC INPUT FUSE (480 VAC INPUT ONLY)
T1	POWER ISOLATION TRANSFORMER	L2	FILTER INDUCTOR
TB3	SUMMARY ALARM CONTACTS	R9	FILTER CAPACITOR (C1) BLEED RESISTOR
TB5	RESISTOR TERMINAL BLOCK	TB4	AUXILIARY ALARM RELAY TERMINAL BLOCK
TB8	TEMPCO PROBE (A10) TERMINAL BLOCK	TB6	MED/HIGH AIC CIRCUIT BREAKER JUNCTION BLOCK
VR1	DC OUTPUT SURGE SUPPRESSOR (- TO +)	VR3	AC LIGHTNING ARRESTOR (LOCATED BEHIND I/O)
VR2	AC INPUT SURGE SUPPRESSOR (L1 TO L2)		



REV	ECN No	DATE	APP	THIRD ANGLE PROJECTION	TITLE	DRAWING No	REV	SHEET	OF
2	E2029	042805		DRAWN BY MCR	022703	AT10.1 SERIES BATTERY CHARGER (OPTIONAL)	2	1	1
1	E1742	091004	GRB	APPROVED	022803	INTERNAL COMPONENT LAYOUT: STYLE-586/594			
0	E1154	022703		UNLESS OTHERWISE NOTED DIMENSIONS ARE IN INCHES. TOLERANCES ARE:		JE5027-99			
						SCALE NTS		PART No JE5027-99	